

PRODUCT-DETAILS

CTA/80

CTA/80 Current transformer



General Information

Extended Product Type	CTA/80
Product ID	2CSG111110R1141
EAN	8012542662105
Catalog Description	CTA/80 Current transformer
Long Description	CTA/80 is used to transform primary currents to..../5A secondary currents for c.a. measurement instruments

Technical

Product Name	Current transformer
Cable Use	Cable
Rated Primary Current (I _{pn})	80 A
Rated Secondary Current (I _{sn})	4 A
Current Limit Function	FS 5
Frequency (f)	50 ... 60 Hz
Secondary Output Connection	Screw connection
Accuracy	±0,5%
Mounting Type	Wound primary
Model Number	Through-feed current converter

Environmental

Ambient Air Temperature	Operation -5 ... 50 °C
RoHS Status	Following EU Directive 2002/95/EC August 18, 2005 and amendment
Environmental Information	See RoHS Information

Dimensions

Product Net Width	56 mm
Product Net Height	26.5 mm
Product Net Depth / Length	63 mm
Product Net Weight	0.355 kg

Container Information

Package Level 1 Units	box 1 piece
Package Level 1 Width	0.083 m
Package Level 1 Height	0.063 m
Package Level 1 Depth / Length	0.056 m
Package Level 1 Gross Weight	0.377 kg
Package Level 1 EAN	8012542662105

Ordering

Minimum Order Quantity	1 piece
Customs Tariff Number	85043121
Country of Origin	Italy (IT)
Selling Unit of Measure	piece

Certificates and Declarations (Document Number)

Declaration of Conformity - CE	9AKK106713A5700
Environmental Information	See RoHS Information
Instructions and Manuals	2CSC446012B0201
RoHS Information	2CSC445013K0201

Popular Downloads

Data Sheet, Technical Information	9AKK107046A0430
Instructions and Manuals	2CSC446012B0201

Classifications

ETIM 6	EC002048 - Current transformer
ETIM 7	EC002048 - Current transformer
ETIM 8	EC002048 - Current transformer
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)

WEEE B2C / B2B	Business To Consumer
CN8	85043121
Object Classification Code	T

Categories

Low Voltage Products and Systems → Modular DIN Rail Products → Energy Efficiency Devices → Current Transformers

